

For Your Information ...

Using GRAFIK Eye QS to Power More Than Three Wallstations




Overview

This application note details the proper wiring configuration to add an additional power supply (Lutron P/N: GRX-12VDC) to power seeTouch® QS wallstations when more than three wallstations need to be connected to one *GRAFIK Eye* QS. This information is a supplement to the wiring details found in the *GRAFIK Eye* QS installation guide. This power supply is capable of delivering enough power for 12 seeTouch QS wallstations. The maximum distance between this power supply and any of the wallstations it is powering is 300 feet. This power supply has a two conductor cable for its output. The conductor with the white stripe is the +12 VDC and the other conductor is the COMMON

Wiring Details

An external 12 V=== Power Supply is required to power more than three wallstations from a single control unit.



The +12 VDC wire from the power supply connects to QS link terminal 2 on all of the wallstations it is powering. This wire does not connect to terminal 2 on the *GRAFIK Eye* QS.

The COMMON wire from the power supply connects to QS link terminal 1 on all of the wallstations it is powering and terminal 1 on the *GRAFIK Eye* QS.

The communication signals on the QS link (terminals 3 and 4) connect from the wallstations to the *GRAFIK Eye* QS on twisted, shielded cable just as when an additional power supply is not being used.

Power Supply

Lutron Part #: GRX-12VDC Input: 120 V ∼ 60 Hz

Output: 12 V=== 0.8 A PELV (Class 2: USA)

Description: 120 V \sim to 12 V=== plug-in power supply, capable of delivering 0.8 A with

PELV (Class 2: USA) rated output

Worldwide Technical and Sales Assistance

If you need assistance, call the toll-free **Lutron Technical Support Center.**Please provide exact model number when calling. 24 hours/day + 7 days/week

North and South America

U.S.A., Canada, Caribbean: 1.800.523.9466

Mexico: +1.888.235.2910

Central/South America: +1.610.282.6701

<u>Europe</u>

Technical support: +44.(0)20.7680.4481

<u>Asia</u>

Northern China: 10.800.712.1536 Southern China: 10.800.120.1536

Hong Kong: 800.901.849 Indonesia: 001.803.011.3994 Japan: +81.3.5575.8411

Macau : 0800.401 Singapore: 800.120.4491 Taiwan: 00.801.137.737

Thailand: 001.800.120.665853 Other countries: +65.6220.4666

Visit us on the web at www.lutron.com

Lutron Electronics Co., Inc. 7200 Suter Road

Coopersburg, PA 18036-1299 U.S.A.

Phone: (610) 282-3800 Fax: (610) 282-3090

Made and printed in U.S.A. 08/07 P/N 048-208 Rev A.